



1CMMR

1 Channel Standard Multitek Mains Receivers

Now you can turn on the outside lights, the sprinkler system, the pool pump...well now you can turn on literally anything by pressing your remote control from a distance! The Mains Receiver works in the same way as a standard receiver, with the added feature of a single relay output for a direct connect to any device that operates on 220V AC. Encased in a durable, waterproof casing, this is a real convenient prize winner!

Features:

Relay can be selected between pulse and latch

Relay rated at 5 amp, 220 volt output relay

Built in field strength LED to assist with installation

Unique advanced interference reduction circuit

Incorporates Multitek Smart Memory

Compatible with Binary, Trinary, French Rolling Code & Code Hopping



1CMMR

1 Channel Standard Multitek Mains Receivers

Dimensions:

Length: 8.5cm

Width: 8.5cm

Depth: 2.8cm

Specifications:

SENSITIVITY:

1 μ V

SUPPLIED VOLTAGE:

180 - 250V AC

RELAY CONTACTS:

12 amp

RELAY CONTACTS VOLTAGE:

220V AC

COMPATIBILITY WITH:

Binary, Trinary, French Rolling Code

FREQUENCY:

403.55 Mhz

433.92 Mhz

and others on request



Tel: +27 (0)11 396 2720 / 0861 BARTRON

Fax: +27(0)11 396 2727

Web: www.bartronics.co.za

38 Pomona Road, Pomona Estates, Kempton Park

GPS Co-ordinates: S 26 05.362 E 28 16.407

P.O. Box 12188

Aston Manor

1630

South Africa